

Ceasefire Instalert

Stop fire. Stop theft.

Most buildings, offices, factories and commercial premises have been armed with fire extinguishers. Unfortunately, in the event of a fire, most of these extinguishers wouldn't be able to batter the flames. In some cases, the extinguishers have been vandalised or misused, making them useless. In others, the extinguishers have been stolen.

The answer isn't replacing or recharging these fire extinguishers. All you need is a device that can protect the extinguisher 24x7. So that in the case of an emergency, the extinguisher works perfectly to put out the flames and save lives.

Ceasefire's Instalert makes such a tamper-proof device.



How Instalert works



Sturdy and self-contained, the Ceasefire Instalert has a highly visible 'stop sign' design to discourage wrongful use and tampering. To add to this, if the fire extinguisher is moved, an integral sounder emits a piercing alarm. This not only dissuades thieves, it also alerts people in case of a fire.

Instalert is easy to install and comes with a deactivation cable so that the extinguisher can



be serviced with ease. It also comes with an operating cable kit and a 9V PP3 alkaline battery. Instalert has been designed to ensure the extinguisher is totally accessible for emergencies and will not interfere in the event of a real fire. It can even be installed on an existing fire extinguisher.



Features of the Ceasefire Instalert

-  Highly visible 'stop sign' design is effective in helping stop theft, misuse or vandalism
-  Sounds a powerful 98dB (at 1 metre) warning alarm when activated (low volume setting also available)
-  Self-contained 9V DC alkaline power source
-  Indestructible polycarbonate housing
-  Compact design (136mm/5.35" dia x 50mm/1.97" deep) mounts easily next to the extinguisher
-  Remote powered 12V or 24V DC models
-  Deactivation cable provided for service



Technical Specifications:

Housing:	3mm/1/8" polycarbonate
Dimensions:	136mm/5.35" (height) x 136mm/5.35" (width) x 50mm/1.97" (depth)
Power Source:	9V DC alkaline
Sounder Output:	95dB - low / 98dB – high (at 1 metre)
Operating Cable:	3mm/1/8" galvanised steel
Standby Current:	None
Alarm Current:	40mA at 95dB / 150mA at 98dB

Accessories:

- Operating cable kit (includes operating cable and seal)
- Service/deactivation cable
- Tamper key

Ceasefire Instalert comes with everything you need to safeguard a single extinguisher.



To get 360° protection, call our toll free hotline: **1800 11 3473 / 1800 180 7233** or call **+91-120-4223473** or SMS **FIRE** to **53030**
CEASEFIRE INDUSTRIES PVT. LTD. PLOT NO. - 4, SECTOR - 135, NOIDA - GREATER NOIDA EXPRESSWAY, NOIDA - 201301, UTTAR PRADESH (INDIA). Tel.: +91-120-7154114 Fax: + +91-120-7154115 | Web: www.ceasefire.in | Email: response@ceasefire.in

